
Release Notes – Android Jellybean (MPA3) - Fusion A3.01.0.0.057R

Contents

[Description](#)

[Device Compatibility](#)

[Installation Instructions](#)

[Version History](#)

[Downloadable Software included in this Release](#)

Description

Fusion is a suite of software, which allows for WLAN connectivity, configuration, status reporting, and diagnostics. This is a release of Fusion A3.01.0.0.057R for all Android JB products. (MC32, MC40 and MC67).

- Added Fix to protect from KRACK Vulnerability.

Device Compatibility

This software release has been approved for use with the following Zebra devices.

Device	Operating System
MC32, MC67 and MC40	MC32: Jellybean BSP 5 MC67: Jellybean BSP 06.01.16 MC40: Jellybean BSP 04.11.0610

Installation Instructions

NOTE: Prior to installation, ensure that you are currently running an approved version of the Operating System from the table above. Otherwise, visit <https://www.zebra.com/us/en/support-downloads>

Manual Installation (MC32)

1. Copy the release .zip onto the root directory on a SD card.
2. Insert SD into MC32.
3. Press and hold 1+9+Power Key. Unit will reboot at this point
4. Release 1+9+ Power keys and hold gun trigger while unit boots
5. When Android logo appears on the screen release trigger key

6. Press Home key to launch Recovery menu
7. Use up and down arrows to navigate and enter key to select menu items
8. Select "apply update from sdcard"
9. Select the release .zip file package on /sdcard
10. Note: battery must have at least 30% charge for the update to proceed
11. When the update is completed select "reboot system now"

Manual Installation (MC67)

1. Connect the USB cable from your PC to the device and enable USB mass storage mode on the device.
2. On your PC, you should see an internal and external USB mass storage drive (SD card) appears in the File Explore and copy the recovery update zip file to any storage.
3. Press and hold 1+9+Power Key. Unit will reboot at this point.
4. Keep holding down PTT Trigger. (Release 1+9+ Power Button at this point.)
5. The Android logo should appear on screen. Release PTT Trigger.
6. Press Home key to launch the Recovery menu
7. Click on Vol+ or Vol- to navigate and select appropriated storage
8. Click on PTT Trigger to select the option
9. Click on Vol+ or Vol- to navigate to the recovery update zip file
10. Click on PTT Trigger to select the recovery update zip file

Manual Installation (MC40)

1. Connect the USB cable from your PC to the device
2. Make sure MTP mode is selected in the USB settings in the device and MTP drivers are installed in your PC.
3. The internal SD card of MC40 will be seen in your PC as mounted drive MC40N0.
4. Copy the FusionUpdatePackage_MPA3_JB_A_3.01.0.0.056R.zip file to the root folder on internal SD card.
5. Press and hold the Power button on the device until the Device options menu appears.
6. Tap on Reset to reboot the device.
7. When the device is rebooting hold the left Scan/Action button to enter Recovery update mode.
8. When the Recovery Mode home screen (Android logo) appears then release the left Scan/Action button.
9. Touch Home button to enter Recovery menu screen.
10. Click on Vol+ or Vol- to navigate to the "apply update from sdcard" option.
11. Click on PTT key to select the option.
12. Click on Vol+ or Vol- to navigate to the recovery update zip file.
13. Click on PTT key to select the recovery update zip file.
14. Click on Vol+ or Vol- to navigate "reboot system now" and Click on PTT key to reboot the device

Version History

FUSION_A_3.01.0.0.056R, August 2017

Bugs Fixed:

- Added support for ETSI RE-D compliance.

FUSION_A_3.01.0.0.055R, July 2017

Bugs Fixed:

- Fix added to prevent the device from being exposed to KRACK Vulnerability.

Downloadable Software Included in this Release

Filename	Description
FusionUpdatePackage_MPA3_JB_A_3.01.0.0.057R.zip	Recovery package update for Fusion Release for MC32, MC67 and MC40 (Jellybean Products)